
specificazioni	
Numero di parte	GRM0335C2AR80BA01D
fabbricante	Murata Electronics
Descrizione	CAP CER 0.8PF 100V C0G/NP0 0201
Categoria	condensatori > Condensatori ceramici
Stato parte	2554 pcs Stock
Tensione - nominale	100V
Tolleranza	±0.1pF
Spessore (max)	0.013" (0.33mm)
Coefficiente di temperatura	C0G, NP0
Dimensioni / Dimension	0.024" L x 0.012" W (0.60mm x 0.30mm)
Serie	GRM
Giudizi	-
imballaggio	Tape & Reel (TR)
Contenitore / involucri	0201 (0603 Metric)
temperatura di esercizio	-55°C ~ 125°C
Tipo montaggio	Surface Mount, MLCC
Tipo conduttore	-
Distanza conduttori	-
Altezza - In sede (max)	-
Caratteristiche	-
Capacità	0.8pF
applicazioni	General Purpose

Potresti essere anche interessato:

GRM0335C2AR60BA01D Murata Electronics North America CAP CER 0.6PF 100V C0G/NP0 0201	GRM0335C1E1R0BA01D MURATA GRM0335C1E1R0BA01D MURATA	GRM0336R1E100JD01D Murata Electronics North America CAP CER 10PF 25V R2H 0201	GRM0335C2AR90BA01D Murata Electronics North America CAP CER 0.9PF 100V C0G/NP0 0201
GRM0335C2AR40BA01D Murata Electronics North America CAP CER 0.4PF 100V C0G/NP0 0201	GRM0335C2AR50BA01D Murata Electronics North America CAP CER 0.5PF 100V C0G/NP0 0201	GRM0335C2AR70BA01D Murata Electronics North America CAP CER 0.7PF 100V C0G/NP0 0201	GRM0335C2AR70BA01D Murata Electronics North America CAP CER 0.7PF 100V C0G/NP0 0201

GRM0335C2AR80BA01D Parola chiave correlata

Di Più

GRM0335C2AR80BA01D Murata Electronics	Scheda tecnica GRM0335C2AR80BA01D	Schede tecniche GRM0335C2AR80BA01D	GRM0335C2AR80BA01D PDF	Murata Electronics GRM0335C2AR80BA01D
GRM0335C2AR80BA01D elettronico	Componenti GRM0335C2AR80BA01D	Distributore GRM0335C2AR80BA01D	Immagine GRM0335C2AR80BA01D	GRM0335C2AR80BA01D Part
GRM0335C2AR80BA01D Prezzo	GRM0335C2AR80BA01D Produttore	Immagine GRM0335C2AR80BA01D	Stock GRM0335C2AR80BA01D	Inventario GRM0335C2AR80BA01D
GRM0335C2AR80BA01D Nuovo	GRM0335C2AR80BA01D Originale	GRM0335C2AR80BA01D garantito	GRM0335C2AR80BA01D RFQ	GRM0335C2AR80BA01D Ordina online